

Windows 98 Installation

1
step

Install the Driver/Update Utility

Install the IntelliTouch Driver host application by first downloading the file from http://www.onholdplus.com/drivers/OHP6000_FW_v.2.001.zip. Extract the file and double-click setup. Once the installation is complete, InstallShield will prompt you to reboot the machine.

2
step

Put the Device in Recovery Mode

After the reboot, put your device in recovery mode by turning the device on while holding the play button for 10 seconds. The player's LCD will remain blank.

3
step

Run the Update Utility

Run the update utility from the start menu. Start - Programs - IntelliTouch MP3 Player 6000 Series - MP3 6000 Series Update. At this stage, a progress bar goes across the screen (which means that firmware is being copied on the RAM).

4
step

Load the Firmware

Now, run the update utility for the second time. At this stage, the updater GUI shows up. You should now run the GUI (hit 'start' on the GUI) to load the firmware to the ROM. **Note:** that this 2nd step is needed to write the configuration to permanent memory. If you reboot after the first step, the firmware on the RAM is lost.

For technical support call (858) 320-6737

On-Hold Plus™

IntelliTouch Communications
5160 Carroll Canyon Road
San Diego, CA 92121
858-457-3300 FAX 858-457-3311
www.onholdplus.com